

Job	Type
-----	------

Dimensions

Remote Ballast Box

A	B	C	D
20.37"	41.0"	8.75"	45.5"
518 mm	1041 mm	222 mm	1156 mm

SHIPPING WEIGHTS — Ballast Quantity / Enclosure

	1		2		3		4		5		6	
wattage	lbs.	kg	lbs.	kg	lbs.	kg	lbs.	kg	lbs.	kg	lbs.	kg
1000	110	50	131	60	152	69	173	79	194	88	215	98
1500	120	55	151	69	182	83	213	97	244	111	275	125

Specifications

Construction
Hot-dip galvanized 14 gauge steel to ASTM A123 standards. Isolated ballast/capacitor chambers. EPDM gasketing. Lockable stainless steel latches. Galvanized hinges. Water tight wire entry. Built in pole mounting bracket. Two compartment design. Labeled for easy reference.

Electrical
Ballast/capacitor/fusing included. Factory pre-wired. Thermal magnetic or load breakers. Landing lug provided. Terminal block. Double or single fusing. Wiring harness plug in connector. Wiring schematic included. Isolated ballast/capacitor chambers.

Special Features
Designed as a system. UL 1598 listed and CSA NRTL/C certified to 40°C ambient. Switch level dimming optional. 100% factory electrically tested.

Ordering Information

Fixture Data

series	watt	voltage	ballast qty.	options	options
REM					

SERIES		VOLTAGE		BALLAST QTY.	
REM	Remote	5	480V	31⁴	Four ballast, 2 circuit, 3 & 1
REM D³	Remote Dual Box	6	347V	32⁴	Five ballast, 2 circuit, 3 & 2
WATT		BALLAST QTY.		OPTIONS	
1000H	1000W Metal Halide	1	One ballast	33⁴	6 Ballast, 2 circuit, 3 & 3
1500H	1500W Metal Halide	2	Two ballast	41⁴	5 Ballast, 2 circuit, 4 & 1
VOLTAGE		3	Three ballast	42⁴	6 Ballast, 2 circuit, 4 & 2
2⁶	208V	4	Four ballast	51⁴	6 Ballast, 2 circuit, 5 & 1
3	240V	5	Five ballast	SH	Solutions Harness wiring
4	277V	6	Six ballast	SD1¹	Switch level dimming 120V control
		11⁴	Two ballast, 2 circuit, 1 & 1	SD2¹	Switch level dimming 24V control
		21⁴	Three ballast, 2 circuit, 2 & 1	TB²	Thermal magnetic breaker
		22⁴	Four ballast, 2 circuit, 2 & 2	T	Three Phase
				WP⁵	Wall or Wood Pole Mounting

1. Consult factory.
 2. Load break switch is standard on 277V, 480V and 347V. Thermal magnetic breakers are standard on 208V and 240V.
 3. Used for switching.
 4. Used with REMD Series only.
 5. Ballast secondary leads wired to terminal blocks.
 6. Must order REMD Series with "33" ballast quantity when ordering six luminaires at 208V single phase.

Comments